

PC1011PIII Pre-amplifier



Features

- Various and multiple input/output ports: 1 unbalanced priority microphone port; 2 unbalanced microphone ports; 2 balanced microphone ports; 3 audio source unbalanced input ports; 2 audio source balanced input ports; 2 EMC emergency input ports; 4 output ports.
- Full touch button operation.
- Independent volume control for each channel, and total volume control.
- Treble and bass tone control.
- The LCD with high illuminance for volume scale position and value of each channel, signal dynamic amplitude, treble and bass tone scale position.
- With priority function, and automatic mute (with override function).
- Support PC remote control.
- With address setting function, a system can connect a maximum of 16 units.
- With built-in chime generator.

Specification

Nominal Input	Mic1, 2, 3: 600Ω, 5mV, unbalanced Mic4,5: 600Ω,5mV, balanced EMC1, 2; Aux1, 2, 3: 10kΩ, 300mV, unbalanced Aux4,5: 10kΩ, 300mV, balanced
Nominal Output	0dBV
Frequency Response	20Hz-20kHz(±3dB), line input
THD	Aux: 0.05%, Mic: 0.3%(0dB)
SNR	Mic input: >70dB Aux input: >70dB
Tone	Bass: ±10dB (100Hz) Treble: ±10dB (10kHz)
Chime	Each time press the button, the melody is “(1-3-5-i-)”, with adjustable volume.
Protection	AC fuse×1 (220V: F0.6AL, 110V: F1AL)
Power Supply	AC220V/50Hz
Package Dimension (mm)	(L×W×H) 555×455×185
Machine Dimension (mm)	(L×W×H) 484×320×88
Gross Weight	7.9kg
Net Weight	6.1kg